



# SINUS UPS

SIN UPS 200W S

350-207

Publication date 2023-12-04



# Table of Contents

|  |    |
|--|----|
| 1. About Sinus UPS from Milletechnik .....   | 4  |
| 1.1. About translation of this document .....  | 4  |
| 2. Component overview .....  | 5  |
| 3. Enclosures .....  | 5  |
| 3.1. Wall mounting .....   | 5  |
| 3.2. Mounting .....  | 6  |
| 4. Connection 230 V .....  | 6  |
| 4.1. In: Battery connection .....  | 6  |
| 4.2. Load disconnecter incoming mains (in: 230 V) .....                                    | 7  |
| 5. Out: 230 V .....  | 7  |
| 6. Microsinus .....  | 7  |
| 6.1. Short description: Microsinus .....   | 7  |
| 7. Alarm connection .....  | 8  |
| 8. Commissioning - how to start the unit .....   | 8  |
| 9. Care instructions UPS .....   | 8  |
| 9.1. Battery replacement UPS .....   | 8  |
| 10. Dimensioning UPS .....   | 9  |
| 11. Alarm / status on indicator diode .....  | 9  |
| 12. Front panel and status indicators .....  | 10 |
| 13. FAQ UPS .....  | 10 |
| 13.1. Control measures in case of alarm UPS - Overvoltage, too high charging current ..... | 10 |
| 13.2. Test load in UPS (part of self-test system) .....                                    | 10 |
| 13.3. Are alarms given when batteries are recharged after a power outage? .....            | 11 |
| 13.4. Technical facts alarm: Overvoltage .....   | 11 |
| 14. SIN .....  | 11 |
| 14.1. SIN - UPS Product sheet / technical data .....                                       | 11 |
| 14.1.1. Technical specifications .....   | 11 |
| 14.1.2. SINUS UPS name, article number and e-number .....                                  | 11 |
| 14.1.3. Maximum rated power .....  | 11 |
| 14.1.4. ABOUT UPS .....  | 12 |
| 14.1.5. Fixed installation .....   | 12 |
| 14.2. Areas of use .....   | 12 |
| 14.3. Regulations and certifications .....   | 12 |
| 14.3.1. Requirements that the product meets .....  | 12 |
| 14.4. Circuit boards - Technical data .....  | 13 |
| 14.4.1. Technical data: CEO 3 .....  | 13 |
| 230 V voltage in .....   | 13 |
| 230 V output voltage .....   | 13 |
| Battery charge .....   | 13 |
| Protection .....   | 13 |
| Fuses Minisinus v8 .....   | 14 |
| Self-test .....  | 14 |
| Alarm .....  | 14 |
| Alarm Microsinus - in detail .....   | 14 |
| 14.5. Technical data enclosures .....  | 14 |
| 14.5.1. Enclosures - Technical Data S .....  | 14 |
| 14.6. Batteries - recommended, not included .....  | 15 |
| 14.6.1. Batteries are not included they are sold separately .....                          | 15 |
| 14.6.2. 7.2 Ah, 12 V AGM battery .....   | 15 |
| 14.7. Link to the latest information .....   | 15 |
| 14.8. Warranty, support, country of manufacture and country of origin .....                | 15 |
| 14.8.1. Warranty .....   | 15 |
| 14.8.2. Manufacturer support .....   | 16 |



|  |    |
|--|----|
| 14.8.3. Support .....                                  | 16 |
| Spare parts .....                                      | 16 |
| Support after the warranty period .....                | 16 |
| Questions about product performance? .....             | 16 |
| 14.8.4. Contact us .....                               | 16 |
| 14.8.5. Country of manufacture .....                   | 16 |
| 14.8.6. Designed and produced by: Milleteknik AB ..... | 16 |
| 15. Address and contact details .....                  | 17 |

## 1. ABOUT SINUS UPS FROM MILLETEKNIK

The SIN inverter is an Off-line UPS that steps in and replaces the supply from the mains in the event of a mains failure, until the mains returns (or the batteries are completely discharged). SIN inverters are designed with the latest switching technology and microprocessor monitoring, for: Highest efficiency and operational reliability, providing long life for both electronics and batteries. Well protected with , protection against overtemperature, overload, short circuit. Complete self-test including advanced battery test. The units are installation and service friendly: Compact volume. Modular structure.

The UPS is charged with a built-in power supply and is powered further by batteries in the event of a power failure.



### **SAFETY - READ THIS FIRST**

- The unit must be installed by a qualified person.
- It is the installer's responsibility that the system is suitable for intended use.
- Documents accompanying the system must be kept in its immediate vicinity.
- The system should not be connected to the mains during installation.
- All information is subject to change.



### **DANGER**

Dangerously high voltage.

Wait one (1) minute after power has been disconnected from the unit.

### 1.1. About translation of this document

User manual and other documents are in the original language in Swedish. Other languages are machine translated and not reviewed, errors may occur.





## 2. COMPONENT OVERVIEW




Table 1. Component overview

| Letter | Explanation                           |
|--------|---------------------------------------|
| A      | Cabinet in powder-coated sheet metal. |
| B      | Battery.                              |
| C      | Motherboard.                          |
| D      | Fuse.                                 |
| E      | Cable entries                         |

## 3. ENCLOSURES


### 3.1. Wall mounting

Use four screws suitable for the wall to mount the cabinet.

The distance between the screw head and the wall should be 1.5–2 mm.

Preferably leave a 100 mm air gap around the unit.





### 3.2. Mounting

Use the appropriate screw for mounting on the wall, Screw for mounting on the wall is not included.

## 4. CONNECTION 230 V

### 4.1. In: Battery connection




Table 2. Overview of incoming mains and battery connection

|   |                |
|---|----------------|
| I | Battery wiring |
|---|----------------|

Connect Phase/Neutral/Earth (PE) incoming on motherboard





## 4.2. Load disconnecter incoming mains (in: 230 V)

For maximum safety, always disconnect from the mains before installation and service. Connect a load disconnecter (circuit breaker) to the incoming cable from the mains. Place it easily accessible and label it clearly. With a load disconnecter installed, incoming voltage can be easily interrupted during service and function tests.

## 5. OUT: 230 V

Output phase/load to PICTO marked 5 on circuit board overview (always voltage out). Output phase/load to (EMERGENCY LIGHT) marked 4 on circuit board overview (only energized in case of mains failure). Output zero, to ZERO, marked 3 on circuit board overview. Protective ground, to GND, labeled 2 on circuit board overview.

## 6. MICROSINUS

### 6.1. Short description: Microsinus




Table 3. Circuit board overview, explanation

| No | On circuit board | Explanation   |
|----|------------------|---|
| 1  | F1               | Charging fuse   |
| 2  | P5:4             | Outgoing protective earth, PE (protective earth).PE                 |
| 3  | P5:3             | Outbound Zero, Zero.  |
| 4  | P5:2             | Outgoing phase/emergency light, 230 V out in case of mains failure. |
| 5  | P5:1             | Output phase/load, always 230 V out.                                |
| 6  | P4: PE           | 230 V in, PE  |
| 7  | P4: N            | 230 V in, N   |
| 8  | P4: L            | 230 V in, Phase   |



| No | On circuit board | Explanation               |
|----|------------------|---------------------------|
| 9  | P1:1-3           | Total alarm, NO, Com. NC. |
| 10 | BAT+/BAT-        | Battery wiring            |

## 7. ALARM CONNECTION

Self-test and alarm for mains failure

Total alarm for self-test: Connect total alarm for self-test (Self Diagnosis).

P1:1-3, incorrect charging voltage (over/undervoltage), aged battery - when the battery should be replaced, or non-functioning inverter to circuit board terminal P1:1-3. Alarm - contact NO and CO.

## 8. COMMISSIONING - HOW TO START THE UNIT

After connection, start-up must take place in the following steps:

Table 4. Commissioning - the order

| Step | Explanation  |
|------|--|
| 1    | Switch the fuse to 0/OFF and open the cabinet.   |
| 2    | Connect input and output cable and alarm.  |
| 3    | Close the cabinet and switch the fuse to ON/1.   |
| 4    | Connect to the mains.  |
| 5    | The system starts up automatically. LED indication on the cabinet door flashes until it lights up solid green. The UPS is commissioned and activated. The load is fed directly from the mains in normal mode and from the batteries via the inverter in battery operation. Switching time is typically 20ms. |
| 6    | Temporarily disconnect mains voltage to test that the UPS is working (connected load continues to be powered in battery mode).   |
| 7    | Reconnect to mains voltage.  |

## 9. CARE INSTRUCTIONS UPS

The unit is maintenance-free when installed in a room temperature indoor environment +15°C—+25°C. However, the batteries should be changed after 10-12 years to maintain high guaranteed safety. In the extended temperature range +5°C—+15°C/+25°C—+30°C, the batteries will age twice as fast. Further colder or warmer ambient temperature means that reliability is at risk.

### 9.1. Battery replacement UPS



#### **WARNING**

Fuse on the lid does not interrupt current (230 V) but only interrupts voltage to batteries (24 V).





| Step | Explanation  |
|------|--|
| 1    | Set fuse "0" and open the cabinet. This disconnects batteries. The device is still energized.  |
| 2    | For safety's sake, also disconnect the mains voltage.  |
| 3    | Disconnect the battery cables and replace the battery. Be careful not to short-circuit the battery! Note and be careful with orientation regarding battery poles +/- and the location of battery cables!   |
| 5    | Connect the battery cables. Be careful not to short-circuit batteries!   |
| 6    | Close the electrical cabinet and set the fuse to "1".  |
| 8    | Reconnect the mains if it has been disconnected.   |
| 9    | The SelfTestSystem starts up automatically. LED indication on the cabinet door flashes until it lights up steady GREEN. The UPS is commissioned and activated. The load is fed directly from the mains in normal mode and from the batteries via the inverter in battery operation. Switching time is 20 ms. |
| 10   | Temporarily disconnect mains voltage to test that the UPS is working (connected load continues to be powered in battery mode).   |
| 11   | Reconnect to mains voltage.  |

## 10. DIMENSIONING UPS

Dimension the connected load so that it is, in total, as large as the inverter's maximum rated power (W), preferably less to partly obtain safety margins, and partly to compensate for losses in connections/cabling and the load which means greater actual power consumption from the inverter than the specified rated power of the load. Take temporary starting power into account, so that it does not exceed the specified maximum - short-term - starting power (VA) of the inverter. Back-up load operation should take place within one hour of the grid failure occurring, as the inverter consumes power at idle, which gradually drains the batteries.


## 11. ALARM / STATUS ON INDICATOR DIODE

Alarm is shown on the indicator diode on the cabinet door.

Mains operation/mains interruption alarm: During normal mains operation, the LED on the front panel is constantly lit. In the event of a mains failure, the inverter starts in battery operation, whereby the LED flashes "1 blink" ORANGE so that when the time for any set time delay of the mains alarm occurs, the LED blinks "2 blinks" ORANGE. In the event of a "mains failure" alarm, the alarm contact switches to contact between NO-CO.



## 12. FRONT PANEL AND STATUS INDICATORS



SIN UPS 200W S

| Indicator diode   | Text   | Explanation                                      |
|-------------------|--|--|
| Green, solid glow | OK   | The device is working normally                   |
| Green blinks      | Mains Failure / Mains Failure  | 230 V mains failure                              |
| Yellow flashes    | Aged batteries / Aged batteries  | Battery needs to be replaced                     |
| Red, solid light  | Over- or under voltage / UPS error / Over- or under voltage or UPS failure | Over temperature, over current or feedback error |
| Black / off       | Deep discharge protection / Deep discharge protection                      | Deep discharge protection has kicked in          |

## 13. FAQ UPS

### 13.1. Control measures in case of alarm UPS - Overvoltage, too high charging current

If the charging voltage in normal operation exceeds 27.9 V, the charging is disconnected.

Check with a multimeter that the device's charge does not exceed 27.9 V.

Contact support for further assistance with adjusting the voltage of the power supply unit.

### 13.2. Test load in UPS (part of self-test system)

The unit is tested weekly against an internal test load. This is to check that the output voltage is sufficient for UPS operation and thus that the batteries are not aged.





### 13.3. Are alarms given when batteries are recharged after a power outage?

No alarms are given when the batteries are charged after a mains failure.

### 13.4. Technical facts alarm: Overvoltage

If the charging voltage in normal operation exceeds 27.9 V, the charging is disconnected. An alarm is also given on potential-free relay switching.

## 14. SIN

### 14.1. SIN - UPS Product sheet / technical data

Figure 1. UPS SINUS 200W S



#### 14.1.1. Technical specifications

These technical specifications are subject to change without notice.

#### 14.1.2. SINUS UPS name, article number and e-number

| Name             | Article number    | E-number  |
|------------------|-------------------|-----------|
| SINUS UPS 200W S | SM01U0011FP002B70 | 52 136 20 |

#### 14.1.3. Maximum rated power

| Maximum rated power | Continuous effect |
|---------------------|-------------------|
| SIN 200W S          | 200 W             |





#### 14.1.4. ABOUT UPS

The UPS are designed with the latest switch technology and microprocessor monitoring, for maximum efficiency and reliability, providing long life for both electronics and batteries. UPS is well protected with protection against overtemperature, overload, short circuit.

- Complete self-test including advanced battery test.

The units are installation and service friendly: - Compact volume.

NOTE! This translation is not verified and the information should always be cross-checked with the swedish original.

#### 14.1.5. Fixed installation

The product is intended for fixed installation. The battery backup must be installed by a qualified installer.

### 14.2. Areas of use

SINUS UPS is mostly used for camera surveillance, PoE switches and other security systems. Sinus UPS is also used for gates and gate control of smaller and larger industrial and garage doors.

- Camera surveillance,
- PoE switches and other security systems.
- Gate and door control of smaller and larger industrial and garage doors.

### 14.3. Regulations and certifications

#### 14.3.1. Requirements that the product meets

|              |  |
|--------------|--|
| EMC:         | EMC Directive 2014 / 30EU  |
| Electricity: | Low voltage directive: 2014/35 / EU<br>EN 62368-1                              |
| CE:          | CE directive according to: 765/2008  |
| Emission:    | EN61000-6-: 2001 EN55022: 1998: -A1: 2000, A2: 2003 Klass B, EN61000-3-2: 2001 |
| Immunity:    | EN61000-6-2:2005, EN61000-4-2, -3, 4, -5, -6, -11                              |
| LVD          | EN60950  |





## 14.4. Circuit boards - Technical data

### 14.4.1. Technical data: CEO 3

| Info                | Explanation  |
|---------------------|--|
| Article title       | CEO3   |
| Product description | CEO 3 is the next generation circuit board for simpler battery backups. Advanced functions that were not previously possible in simpler battery backups are now available as standard. CEO 3 is a reliable heart in simpler battery backups with fewer components than before, which reduces the environmental impact. |
| Measure             | 120 x 55 mm x 52 mm  |
| Voltage form        | Enfas sinus  |
| Fuses               | See table: Fuses   |
| Fuse on output      | 24 V   |
| Outputs             | Output: four load outputs 1-4 which are prioritized load outlets. (= always voltage).  |
| Insurance           | Load output: + secured.  |
| Indication          | Display showing operating status, alarms and faults. Operating indication: one indication diode per load output +/- . Solid green light = normal operation.  |

### 230 V VOLTAGE IN

| Voltage      | Explanation / comment                |
|--------------|--------------------------------------|
| Voltage in:  | 230V -15%, + 20% in mains operation. |
| Mains power: | charger max 0.4A + load.             |

### 230 V OUTPUT VOLTAGE

| Voltage OUT         | Explanation / comment             |
|---------------------|-----------------------------------|
| Voltage out:        | 230 V - 10% in battery operation. |
| Voltage form:       | Single-phase sine voltage.        |
| Efficiency, approx: | 90%                               |
| Idle power, approx: | 10 W                              |

### BATTERY CHARGE

I / O according to DIN 41773 Current limitation.

### PROTECTION

| Type of protection                      | Explanation   |
|---|---|
| Current limitation, electronic:         | Type 300% of rated capacity.  |
| Short-circuit protection:               | Shutdown within 5 sec in case of heavy overload / short circuit according to UPS EN62040-1-1 standard.<br>Automatic restart when mains voltage returns. |
| Depth discharge protection:             | When the battery terminal voltage is less than 19 V.  |
| Overcharge protection:                  | Disconnection of charging voltage during overcharging.  |
| Automatic fuse:                         | Batteries are secured.  |
| Optional: Ground fault circuit breaker: | Can be installed on output (extra protection option according to EN62040-1-1).  |



## FUSES MINISINUS V8

| On circuit boards | Fuse | Explanation  |
|-------------------|------|--------------|
| F1                | T16A | Battery fuse |

## SELF-TEST

| Type of self-test | Explanation   |
|-------------------|---|
| Battery charge    | Continuous monitoring of battery chargers.  |
| Battery aging     | Automatic test loading of batteries under high, short-term discharge current to detect battery aging. The test compares measured battery capacity with programmed values to give an alarm when the battery has lost 20% - 40% capacity of new value and should be replaced. |
| Inverters         | Test load of UPS (corresponding rated power over internal test load) to check function and sufficient output voltage.   |

## ALARM

All alarms occur on potential-free relay switching.

| Alarm type            | Explanation   |
|-----------------------|---|
| Sum Alarm, Self-Test: | Incorrect charging voltage (over- or under-voltage), aged battery that should be replaced or a malfunctioning inverter. |

## ALARM MICROSINUS - IN DETAIL

Table 5. Alarm Microsinus

| Alarm          | Explanation  |
|----------------|--|
| Battery aging: | Battery failure test is activated when the weekly test is performed. The weekly test starts the UPS for 6 seconds and loads the test load after one second. The UPS measures the battery voltage before and at the end of the test. Battery failure is given if the final voltage is lower than 24.0 V or if the voltage decreased by more than 2.5 V before and after the test. |
| Undervoltage:  | Tested every 45 minutes. The battery is disconnected for 100 ms and when the voltage from the power supply is less than 13.45 V (no hysteresis) the alarm is activated.  |
| UPS error:     | Activated when the weekly test is performed. Sources of error: no feedback, overcurrent or overtemperature.  |
| Overvoltage:   | Overvoltage is tested every second and if the system voltage is higher than 13.95 V an alarm is given. Alarm for overvoltage returns when the voltage goes below 13.7 V.   |

## 14.5. Technical data enclosures

### 14.5.1. Enclosures - Technical Data S

| Info                  | Explanation  |
|-----------------------|--|
| Name                  | S  |
| Enclosure class       | IP 20  |
| Measure               | Height: 230 mm, width: 216 mm, depth: 85 mm.                     |
| Height units          | -  |
| Mounting              | Wall   |
| Ambient temperature   | + 5 ° C - + 40 ° C. For best battery life: + 15 ° C to + 25 ° C. |
| Environment           | Environmental class 1, indoors. 20% ~ 90% relative humidity      |
| Material              | Powder coated sheet  |
| Color                 | White  |
| Cable entries, number | 3  |





| Info               | Explanation  |
|--------------------|--|
| Batteries that fit | 1 pc 12 V 2.3 Ah or<br>2 pcs 12 V 2.3 Ah or<br><br>1 pcs 12 V, 7.2 Ah. |
| Place for fan      | No   |

## 14.6. Batteries - recommended, not included

### 14.6.1. Batteries are not included they are sold separately

Batteries are sold separately.

### 14.6.2. 7.2 Ah, 12 V AGM battery

| Fits in          | Number of batteries |
|------------------|---------------------|
| SINUS UPS 200W S | 2                   |

| Battery type                             | V    | Ah     |
|--|------|--------|
| Maintenance-free AGM, lead-acid battery. | 12 V | 7.2 Ah |

Table 6. 10+ Design life \* battery

| Article number | E-number | Article name                                  | Terminal           | Measure. Height width depth | Weight per piece | Make  |
|----------------|----------|---|--------------------|-----------------------------|------------------|-------|
| MT113-12V07-01 | 5230536  | UPLUS 12V 7.2Ah<br>10+ Design Life<br>battery | Flat pin 6.3<br>mm | 151 x 65 x 100<br>mm.       | 2.4 kg           | UPLUS |

\*Design life is the shelf life in years for an unused battery. Environmental factors such as heat and load affect the service life. Batteries that have a durability (+10 Design Life) of 10+ years usually need to be replaced after 5-6 years.

## 14.7. Link to the latest information

Products and software are subject to updates, you will always find the latest information on our website.

[Sinus UPS](#)

## 14.8. Warranty, support, country of manufacture and country of origin

### 14.8.1. Warranty

The product has a two-year warranty, from the date of purchase (unless otherwise agreed). Support during the warranty period can be reached at [support@milleteknik.se](mailto:support@milleteknik.se) or telephone, +46 31-34 00 230. Compensation for travel and / or working hours in connection with locating faults, installing repaired or replaced goods is not included in the warranty. Contact Milleteknik for more information. Milleteknik provides support during the product's lifetime, however, no later than 10 years after the date of purchase. Switching to an equivalent product may occur if Milleteknik deems that repair is not possible. Support costs may (at Milleteknik's discretion) occur after the warranty period has expired.



## 14.8.2. Manufacturer support

Manufacturers provide support for the life of the product, however, for a maximum of 10 years after the date of purchase. Switching to an equivalent product may occur if the manufacturer deems that repair is not possible. Support costs will be added after the warranty period has expired.

## 14.8.3. Support

Do you need help with installation or connections? Our support phone is available: Monday-Thursday 08: 00-16: 00 and Fridays 08: 00-15: 00. Telephone support is closed between 11: 30-13: 15.

You will find answers to many questions at: [www.milleteknik.se/support](http://www.milleteknik.se/support)

Phone: +46 31-340 02 30

Support is open: Monday-Thursday 08:00-16:00, Fridays 08:00-15:00. Closed 11:30-13:15.

## **SPARE PARTS**

Contacted support for questions about spare parts.

## **SUPPORT AFTER THE WARRANTY PERIOD**

Milleteknik provides support during the life of the product, but no longer than 10 years after the date of purchase. Replacement for an equivalent product may occur if the manufacturer deems that repair is not possible. Costs for support and replacement are added after the warranty period has expired.

## **QUESTIONS ABOUT PRODUCT PERFORMANCE?**

Contact sales: 46 31-340 02 30, e-mail: [sales@milleteknik.se](mailto:sales@milleteknik.se)

## 14.8.4. Contact us

Milleteknik AB

Ögärdesvägen 8 B

S-433 30 Partille

Sweden

+46 31-34 00 230

[www.milleteknik.se](http://www.milleteknik.se)

## 14.8.5. Country of manufacture

Country of manufacture / country of origin is Sweden. For more information, contact your seller.

## 14.8.6. Designed and produced by: Milleteknik AB

Designed and produced by Milleteknik AB





## 15. ADDRESS AND CONTACT DETAILS

Milleteknik AB  
Ögärdesvägen 8 B  
S-433 30 Partille  
+46 31 340 02 30  
[www.milleteknik.com](http://www.milleteknik.com)



This page is intentionally left blank.

This page is intentionally left blank.

This page is intentionally left blank.