

PRODUCT SHEET - POWER SUPPLY FROM MILLETEKNIK

Product image



Name, article number and e-number

Name	Item number	E-number (sv)
8 Output Control Module	A-FU002408OP01C	52 137 01

Designation

Fuse cards, with sum-alarm, are used to protect electronic circuits from damage due to overcurrent or short circuit.

Area of use

Used when more load outputs are needed.

Technical description

Controllable fuse card with eight 1-pole fused and controllable outputs. Either the voltage can be activated on individual outputs or separately in the event of an external alarm or an alarm from the motherboard.

Voltage, current and power

Voltage in: 27.3 V DC, (24 V).

Voltage out: 27.3 V DC, (24 V).

Power outlet: 15 A. Max 2 A per output.

Outputs

Eight single-pole fused and controllable outputs. Output has any function, either the voltage is on or off when external alarms are activated or by the motherboard in the event of a power failure.

Alarm

Alarms for fuse failures are forwarded to the battery backup, which displays the alarm on the LED or via communication.

Fuses

Load fuses: Eight F2As.

Indications and communication

The LED on the circuit board shows both information and alarms. The alarms can be forwarded

to battery backup, which shows alarms on the enclosure door and via communication (applies to compatible battery backup).

Weight

Name	Net weight	Weight incl. packaging
Insurance card 8 outputs	0.3 kg	1 kg

Installation requirements

The product must be installed in a compatible product from Milleteknik.

The accessories fits in

Product series	Enclosure size	Number of cards that can fit ^a
EN54, NEO, NOVA	FLX M	2
NEO, NOVA	FLX L	2
19 rack module holders	4U	8
Enclosure only	S	2

^aThe number of cards/accessories that can fit is the total number that can fit in the housing. Electronic and mechanical limitations may exist.

Requirements that the product meets

EMC:	EMC Directive 2014 / 30EU
Electricity:	Low voltage directive: 2014/35 / EU
CE:	CE directive according to: 765/2008
Environment	REACH Regulation: Directive 1907/2006, WEEE Regulation: Directive 2002/96/EC, RoHS Regulation: Directive 2015/863



Guarantee

The product has a two-year warranty against manufacturing defects. Batteries and wearing parts are not covered by warranty.

Manufacturing, lifespan, environmental impact and recycling

Manufactured by Milleteknik in Partille, Sweden.

The product is designed for a long service life, which reduces the environmental impact. End-of-life products are handed over to the nearest recycling centre.

Link to the latest information

Products and software are subject to updates, you will always find the latest information on our website.

[Accessories & options](#)

About this information

All information is published subject to possible errors. This document is updated without notice.