

## TEKNISKA SPECIFIKATIONER

6 Output Module är en avsäkringsmodul med sex avsäkrade lastutgångar. Kontrollera vid beställning att kortet passar till den batteribackup kortet skall installeras i.

## TEKNISKA DATA: 6 OUTPUT MODULE

Info	Förklaring
Kortnamn:	6 Output Module
Produktbeskrivning	6 Output Module är en avsäkringsmodul med sex helt avsäkrade utgångar.
Produkten passar i	EN54 24V 1,5A MX S EN54 24V 5,5A MX M EN54 24V 7,5A MX L
Rekommenderad miljö	Inomhus, klass 1. Omgivningstemperatur: +5°C – 40°C.
Skyddsklass (IP-klass)	IPOX
Mått	95 x 50 mm
Vikt	0,2 kg
Spänning in	27,3 V DC
Antal spänningsingångar	1
Utgående spänning	27,3 VDC (24 V)
Antal avsäkrade (last-) utgångar	6
Typ av säkring / utgång	F1A (glasrörsäkring)
Maxström	10 A
Larm via	Kabel för anslutning till kretskort på EN54 24V 1,5A MX S EN54 24V 5,5A MX M eller EN54 24V 7,5A MX L.
Larm	Säkringsfel
Garantitid	2 år.

### Tillverkningsland

Produkten är tillverkad i EU

Bruksanvisning/produktblad i original: Svenska.

## ADRESS OCH KONTAKTUPPGIFTER

Milleteknik AB  
Ögärdesvägen 8 B  
433 30 Partille  
Sverige  
031-340 02 30  
info@milleteknik.se  
www.milleteknik.se

## TECHNICAL SPECIFICATIONS

6 Output Module is a fusing module with six fused load outputs. When ordering, check that the card fits the battery backup card to be installed in.

## TECHNICAL DATA: 6 OUTPUT MODULE

Info	Explanation
Card name:	6 Output Module
Product description	6 Output Module is a fuse module with six fully fused outputs.
The product fits in	EN54 24V 1.5A MX S EN54 24V 5.5A MX M EN54 24V 7.5A MX L
Recommended environment	Indoors, class 1. Ambient temperature: +5°C – 40°C.
Protection class (IP class)	IP0X
Measure	95 x 50 mm
Weight	0.2 kg
Voltage in	27.3V DC
Number of voltage inputs	1
Output voltage	27.3 VDC (24 V)
Number of protected (load) outputs	6
Type of fuse / output	F1A (glass tube fuse)
Max current	10 A
Alarm via	Cable for connection to circuit board of EN54 24V 1.5A MX S EN54 24V 5.5A MX M or EN54 24V 7.5A MX L.
Alarm	Fuse failure
Warranty period	2 years.

Country of manufacture - EU

Country of manufacture / country of origin is the EU. For more information, contact your seller.

This translation is not verified and should be cross referenced with the swedish original before use.

## ADDRESS AND CONTACT DETAILS

Milleteknik AB  
 Ögärdesvägen 8 B  
 S-433 30 Partille  
 Sweden  
 +46 31 340 02 30  
 info@milleteknik.se  
 www.milleteknik.se